

This Manual is provided by  
***CBTricks.com***

Someone who wanted to help you repair your equipment put together this information.

Royce 1-601 voltage Chart from Ser. 3 Manual  
If you would like to help us put more manuals online support us.

**If you would like to help with this project let us know.**

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

**Thank you for any support you can give.**

## 201-601 Voltage Chart

			<u>RX</u>	<u>TX</u>
Q101	2SC674	Vb	1.0V	
		Vc	6.6V	
		Ve	1.6V	
Q102	2SC710C	Vb	0.8V	
		Vc	8.3V	
		Ve	0.6V	
Q103	2SC711E	Vb	0.2V	
		Vc	3.7V	
		Ve	0V	
Q104	2SC711E	Vb	0.8V	
		Vc	2.0V	
		Ve	0.6V	
Q105	2SC711E	Vb	0.7V	
		Vc	5.0V	
		Ve	0V	
Q106	2SA562Y	Vb	5.0V	
		Vc	0V	
		Ve	6.4V	
Q107	2SC536	Vb(NO SQUELCH)	0V	
		(SQUELCH)	0.7V	
		Vc(NO SQUELCH)	3.3V	
		(SQUELCH)	0.7V	
		Ve(NO SQUELCH)	0V	
(SQUELCH)	0V			
Q108	2SC536	Vb	0.7V	
		Vc	8.8V	
		Ve	2.1V	
Q109	2SC372Y	Vb(NO SQUELCH)	0.6V	
		(SQUELCH)	0V	
		Vc(NO SQUELCH)	3.9V	} 4.3V
		(SQUELCH)	6.1V	
		Ve(NO SQUELCH)	0.4V	
(SQUELCH)	0V			
Q110	2SD467	Vb	0.7V	
		Vc	0.5V	
		Ve	0V	

			<u>RX</u>	<u>TX</u>
Q201	2SC710C	Vb		1.4V
		Vc		13.4V
		Ve		1.2V
Q202	2SC1018	Vb		
		Vc		12.0V
		Ve		
Q203	2SC756A	Vb		
		Vc		12.0V
		Ve		
Q204	2SA562Y	Vb		
		Vc		
		Ve		0V
Q205	2SC536	Vb	0.8V	0.4V
		Vc	3.9V	4.3V
		Ve	6.6V	2.5V
Q206	2SC735Y	Vb		0.7V
		Vc		0.9V
		Ve		0V
Q301	2SD467	Vb	5.0V	4.6V
		Vc	11.0V	11.0V
		Ve	4.8V	4.6V
Q302	TA7062P	(1)	0.7V	0.7V
		(2)	0.1V	0.1V
		(3)	0V	0V
		(4)	11.8V	11.8V
		(5)	11.4V	11.4V
Q303	2SC1173	Vb	0.7V	0.7V
Q304		Vc	13.1V	13.1V
		Ve	0.1V	0.1V