


Programmable Talkback Feature



Alpha 10 Max - Model AM-1000

Programming the AM-1000 TalkBack Feature (Rev 3.0A Up)

- * Press and Hold the **FUNC** Button for two seconds to enter Programming Mode.
- * Press the **FUNC** Button repeatedly until “**TES**” or “**TNS**” appears on the LCD Display.
- * Use the **Clarifier Control** to set these two functions to a **On/Off** state.



When **TES** is **On**, and **ECHO** is **On**, The user can hear his voice through the speaker to properly set the Echo Function. When **ECHO** is **OFF**, the Talkback feature will not work in other modes. Use the **Clarifier Control** to set this feature **On/Off**.



When **TNS** is **On**, and **ECHO** is **Off**, The user can hear his voice through the speaker. The Talkback feature will work on All Modes to check proper operation and control levels. Use the **Clarifier Control** to set this feature **On/Off**.

Note:

This feature is only available in newer Alpha 10 Max Model AM-1000 (Firmware revision v3.0A up) When entering the programming mode, press the FUNC Button repeatedly until display shows the TNS or TES Functions. If these settings are not shown on the display, your firmware version cannot use this option.